

37-V INPUT DC-DC CONVERTERS



Model 1620H-37-13-30

- FOR RAIL-TRANSIT APPLICATIONS
- 13.6-V OR 24-V OUTPUT AT UP TO 400 WATTS
- INPUT SURGE/TRANSIENT PROTECTION AND INPUT-TO-OUTPUT ISOLATION
- -40°C TO +70°C OPERATING TEMPERATURE RANGE (CONVECTION COOLED)
- EXTREMELY RUGGED AND RELIABLE

Model 1620H-37-13-30 and Model 1620H-37-24-16 dc-to-dc converters provide an isolated, regulated and well-filtered output voltage from 37-Vdc electrical systems on rail transit vehicles. Field-proven input-transient protection and extremely rugged mechanical construction make them well suited for powering voice/data radios and other sensitive electronic loads in the harsh railroad vehicle environment.

SPECIFICATIONS

Input Voltage Range

25 Vdc to 45 Vdc

Output Voltage

Model 1620H-37-13-30

13.6 Vdc

Model 1620H-37-24-16

24.0 Vdc

Output Current

Model 1620H-37-13-30

30 amperes @25% duty cycle[†]

20 amperes continuous duty

Model 1620H-37-24-16

16 amperes @25% duty cycle[†]

11 amperes continuous duty

[†](up to 5 minutes in any 20-minute period, with the remainder of the period at less than 50% of this maximum)

Output Voltage Regulation

Versus line: ±1%

Versus load: ±2%

Output Voltage Ripple

Typically less than 20 mV rms

Ambient Temperature Range

-40°C to +70°C (-40°F to +158°F)
 (Convection Cooling)

Isolation

Isolation capable of passing a 2,500-Vdc stress test is provided between the input and output and between the input and chassis.

Protection

Protection against output short circuits and overvoltages is provided electronically. Recovery to normal operating conditions is automatic upon removal of a short-circuit fault. Following an overvoltage shutdown, input power to the converter must be removed and reapplied to resume converter operation.

Protection against accidental reversal of the dc input-voltage polarity during installation is provided by a shunt diode working in conjunction with a user-supplied input fuse or circuit breaker. See section titled "Installation".

Transient-Withstand Capability

Transient input-voltage surges up to 7,000 volts peak, per IEC 571, Paragraphs 3.5 and 5.4, will not harm the converter.

The converter will not be damaged when its input is subjected to high-energy transients as specified in IEC 1000-4-5, Surge Immunity Test, Level 3, applied line-to-line or line-to-chassis.

Input/Output Connections

The input and output connections are provided via heavy-duty barrier-strip terminal blocks that accept lugs for use with #8 hardware. The chassis ground connection is provided by a self-locking #8 sems screw.

Installation

Good installation practice for mobile electronic equipment dictates that input fuses or circuit breakers should be located at the power-source end of the cables feeding the converter. For this reason, no protection devices are built inside the Model 1620H to protect against fault conditions at the input to the converter. Instead, a 30-A fuse or circuit breaker should be installed near the dc-input source in series with the positive (+) input line when this source is negative-grounded or not grounded (floating); or when the dc source is positive-grounded, installed in series with the negative (-) input line.

Mechanical

Size: Dimensions given in inches (mm): 3.25 (83) high x 8.6 (218) wide x 11.25 (286) deep (excluding flanges and terminal block).

Mounting flanges on base are 0.5 (13) wide (each side).

Terminal block extends 0.7 (18) from front panel.

Weight: 8.5 pounds (3.9 Kg)

Mounting: Mounting flanges on base accept six #10 screws, 3 per side on 4.4 (112) hole-center spacing front-to-back and 9.25 (235) side-to-side.

For Additional Information

Telephone: (919) 732-9351

www.wilmoteelectronics.com

Information provided in this bulletin is subject to change without notice.